Radiative Processes

Simon Casassus Astronomía, Universidad de Chile

http:://www.das.uchile.cl/~simon

- I Radiative Transfer
- II Electromagnetic wave propagation
- **III** Radiation
- IV Scattering and Diffraction
- V Free-free, Synchrotron and Compton Scattering
- VI Radiative Transitions



Part II

Electromagnetic wave propagation

Electromagnetic waves

Maxwell Equations

Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic

waves Wave propagation in a

medium Constitutive equations

Kramers-Kronig relations Monochromatic waves



Maxwell Equations Electrodynamic potentials Wave equations Povnting's theorem

2 Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasi-monochromatic waves

3 Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Manual Equation

Maxwell Equations
Electrodynamic potentials

Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a medium

1 Electromagnetic waves Maxwell Equations

Electrodynamic potentials Wave equations Poynting's theorem

2 Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasi-monochromatic waves

3 Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves



Electromagnetic waves

Maxwell Equations

Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum Spectral decomposition

Connection with radiative transfer Polarization Quasi-monochromatic

Wave propagation in a

waves

1.1-Maxwell Equations

tee

 In the MKS system (or S.I.), the equations of electrodynamics are, :

$$\vec{\nabla} \cdot \vec{D} = \rho, \tag{1}$$

$$\vec{\nabla} \cdot \vec{B} = 0, \tag{2}$$

$$\vec{\nabla} \times \vec{E} = -\frac{\partial B}{\partial t},\tag{3}$$

$$\vec{\nabla} \times \vec{H} = \vec{J} + \frac{\partial \vec{D}}{\partial t}.$$
 (4)

- For linear media, $\vec{D} = \epsilon \vec{E}$ and $\vec{B} = \mu \vec{H}$.
- In vacuum, $\epsilon = \epsilon_{\circ}$ and $\mu = \mu_{\circ}$.

Electromagnetic waves Maxwell Equations

Maxwell Equations

Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a

medium Constitutive equations

Constitutive equations
Kramers-Kronig relations
Monochromatic waves

.5

1 Electromagnetic waves

Maxwell Equations

Electrodynamic potentials

Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasi manageremetic wayses

Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves



Electromagnetic waves Maxwell Equations

Electrodynamic potentials

Wave equations Povnting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a medium Constitutive equations Kramers-Kronig relations Monochromatic waves

1.2-Electrodynamic potentials

• Since $\vec{\nabla} \cdot \vec{B} = 0$, we have

$$\vec{B} = \vec{\nabla} \times \vec{A}$$
. (5)

• For \vec{E} , we use Eq. 5 and Eq. 3:

$$\vec{\nabla} \times \underbrace{\left(\vec{E} + \frac{\partial \vec{A}}{\partial t}\right)}_{\equiv -\vec{\nabla} \Phi} = 0, \ \Rightarrow$$

$$\vec{E} = -\vec{\nabla}\phi - \frac{\partial\vec{A}}{\partial t}.$$
 (6)

Electromagnetic waves Maxwell Equations

Electrodynamic potentials Wave equations

Povnting's theorem Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic Wave propagation in a medium

wavee

Constitutive equations Kramers-Kronig relations Monochromatic waves

.7



Maxwell Equations
Electrodynamic potentials

Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves Maxwell Equations

Electrodynamic potentials
Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a medium

- We want to write equations that determine the electrodynamic potentials \vec{A} and Φ .
- Using the Maxwell Equations in vacuum to connect directly with \vec{E} and \vec{B} , we have

$$\vec{\nabla} \cdot \vec{E} = \frac{\rho}{\epsilon_{\circ}} \implies \nabla^{2} \Phi + \frac{\partial}{\partial t} \left(\vec{\nabla} \cdot \vec{A} \right) = \frac{\rho}{\epsilon_{\circ}}, \tag{7}$$

$$\vec{\nabla} \times \frac{1}{\mu_{\circ}} \vec{B} = \vec{J} + \frac{1}{\epsilon_{\circ}} \frac{\partial \vec{E}}{\partial t} \Rightarrow$$

$$\nabla^{2} \vec{A} - \frac{1}{c^{2}} \frac{\partial^{2} \vec{A}}{\partial t^{2}} - \vec{\nabla} \underbrace{\left(\vec{\nabla} \cdot \vec{A} + \frac{1}{c^{2}} \frac{\partial \Phi}{\partial t}\right)}_{\text{term for the Lorentz condition}} = -\mu_{\circ} \vec{J}. \quad (8)$$



Electromagnetic waves

Maxwell Equations

Electrodynamic potentials

Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

waves

Constitutive equations Kramers-Kronig relations Monochromatic waves

9

• If the term highlighted in Eq. 8 is null, which is called the *Lorentz Condition*,

$$\vec{\nabla} \cdot \vec{A} + \frac{1}{c^2} \frac{\partial \Phi}{\partial t} = 0, \tag{9}$$

then we recover the wave equation for the potentials:

$$\nabla^2 \Phi - \frac{1}{c^2} \frac{\partial^2 \Phi}{\partial t^2} = -\frac{\rho}{\epsilon_{\circ}}, \tag{10}$$

$$\nabla^2 \vec{A} - \frac{1}{c^2} \frac{\partial^2 \vec{A}}{\partial t^2} = -\mu_\circ \vec{J}. \tag{11}$$

 To fulfill the Lorentz condition, we use the freedom of gauge:

$$\vec{A} \longrightarrow \vec{A}' = \vec{A} + \vec{\nabla}\Lambda,$$
 (12)

which leaves invariant $\vec{B} = \vec{\nabla} \times \vec{A}$.

• To also preserve $\vec{E} = -\vec{\nabla}\Phi - \partial\vec{A}/\partial t$, it is necessary that

$$\Phi \longrightarrow \Phi' = \Phi - \frac{\partial \Lambda}{\partial t}.$$
 (13)



Electromagnetic waves Maxwell Equations Electrodynamic potentials

Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

waves

Wave propagation in a medium

- If \vec{A} and Φ both fulfill the general potential equations (Eqs. 8 and 7), but do not fulfill the Lorentz condition, then we can search for $\Lambda(\vec{x},t)$ so that \vec{A}' and Φ' do satisfy the Lorentz condition.
- Injecting Eqs. 12 and 13 in Eq. 9, we reach an equation for $\Lambda(\vec{x},t)$:

$$\vec{\nabla} \cdot \vec{A} + \frac{1}{c^2} \frac{\partial \Phi}{\partial t} + \nabla^2 \Lambda - \frac{1}{c^2} \frac{\partial^2 \Lambda}{\partial t} = 0, \tag{14}$$

which is essentially a wave equation with a source term, i.e. exactly the type of equations that we will propose solutions for.



Electromagnetic waves Maxwell Equations Electrodynamic potentials

Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization

Quasi-monochromatic waves

Wave propagation in a medium

tee

• Independently of the Lorentz condition, we can manipulate the Maxwell equations to reach (tarea):

$$\nabla^2 \vec{E} - \frac{1}{c^2} \frac{\partial^2 \vec{E}}{\partial t^2} = -\frac{1}{\epsilon_o} \left(-\vec{\nabla} \rho - \frac{1}{c^2} \frac{\partial \vec{J}}{\partial t} \right), \quad (15)$$

$$\nabla^2 \vec{B} - \frac{1}{c^2} \frac{\partial^2 \vec{B}}{\partial t^2} = -\mu_{\circ} \vec{\nabla} \times \vec{J}, \tag{16}$$

which are both wave equations with source terms.

 Away from the sources, i.e. in vacuum, both equations become the homogeneous wave equation.

Electromagnetic waves Maxwell Equations Electrodynamic potentials

Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a

medium Constitutive equations



Maxwell Equations Electrodynamic potentials Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasi manageremetic wayses

Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves Maxwell Equations

Electrodynamic potentials
Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a medium

- The power exerted by the electromagnetic force $\vec{\mathcal{F}} = q\vec{v} \times \vec{B} + q\vec{E}$ on a single charge q with velocity \vec{v} is $\vec{v} \cdot \vec{\mathcal{F}} = q\vec{v} \cdot \vec{E}$.
- The power exerted on the charge density distribution ρ and on the current density distribution $\vec{J} = \rho \vec{v}$ inside a volume $d\mathcal{V}$ is thus

$$dP = \vec{J} \cdot \vec{E} \, d\mathcal{V}$$

• The total power exerted by the (\vec{E}, \vec{B}) field on the charges inside a volume \mathcal{V} is

$$P = \int_{\mathcal{V}} \vec{J} \cdot \vec{E} d^3 x. \tag{17}$$



Electromagnetic waves Maxwell Equations Electrodynamic potentials Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

waves

Wave propagation in a medium

We want to connect P with the energy stored in the fields.
 Using the Ampère-Maxwell equation (Eq. 4) we solve for J, and following standard handling (tarea),

$$P = \int_{\mathcal{V}} \left[-\vec{\nabla} \cdot (\vec{E} \times \vec{H}) + \vec{H} \cdot (\vec{\nabla} \times \vec{E}) - \vec{E} \cdot \frac{\partial \vec{D}}{\partial t} \right] d^3 x.$$
(18)

• Now with the induction law, $\vec{\nabla} \times \vec{E} = -\frac{\partial \vec{B}}{\partial t}$ (Eq. 3),

$$P = \int_{\mathcal{V}} \left[-\vec{\nabla} \cdot (\vec{E} \times \vec{H}) - \vec{H} \cdot \frac{\partial \vec{B}}{\partial t} - \vec{E} \cdot \frac{\partial \vec{D}}{\partial t} \right] d^3 x. \quad (19)$$



Electromagnetic waves Maxwell Equations

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum Spectral decomposition

Connection with radiative transfer
Polarization
Quasi-monochromatic

waves

Wave propagation in a medium

Remembering that for a linear medium

$$\vec{H} \cdot \frac{\partial \vec{B}}{\partial t} = \frac{1}{2} \frac{\partial}{\partial t} (\vec{H} \cdot \vec{B})$$
, and $\vec{E} \cdot \frac{\partial \vec{D}}{\partial t} = \frac{1}{2} \frac{\partial}{\partial t} (\vec{E} \cdot \vec{D})$, we reach

$$P = \int_{\mathcal{V}} \vec{J} \cdot \vec{E} d^3 x = -\int_{\mathcal{V}} \left[\frac{\partial u}{\partial t} + \vec{\nabla} \cdot \vec{S} \right] d^3 x, \tag{20}$$

where we recognize

$$u = \frac{1}{2}\vec{E} \cdot \vec{D} + \frac{1}{2}\vec{B} \cdot \vec{H}, \tag{21}$$

and

$$\vec{S} = \vec{E} \times \vec{H}. \tag{22}$$

• For any volume V, we conclude that

$$\frac{\partial u}{\partial t} + \vec{\nabla} \cdot \vec{S} = -\vec{J} \cdot \vec{E}. \tag{23}$$



Electromagnetic waves

Maxwell Equations

Electrodynamic potentials Wave equations

vacuum

waves

Poynting's theorem Wave propagation in

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

• In the same way as for energy conservation, Eq. 23, we can also write the equation for the conservation of linear momentum. Newton's 2nd law for the variation of linear momentum $\delta \vec{p}_{\text{mec}}$ inside a volume $\delta \mathcal{V}$ is:

$$\frac{d \,\delta \vec{p}_{\text{mec}}}{dt} = \rho \vec{E} \delta \mathcal{V} + \rho \vec{v} \times \vec{B} \delta \mathcal{V}. \tag{24}$$

In total,

$$\frac{d\vec{p}_{\text{mec}}}{dt} = \int_{\mathcal{V}} d^3x (\rho \vec{E} + \rho \vec{v} \times \vec{B}). \tag{25}$$



Electromagnetic waves Maxwell Equations

Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a

medium Constitutive equations

• Using Maxwell's equation to replace ρ and \vec{J} , we reach (tarea):

$$\frac{d}{dt}(\vec{p}_{\text{mec}} + \vec{p}_{\text{fields}})|_{i} = \sum_{j} \int_{\mathcal{V}} d^{3}x \frac{\partial T_{ij}}{\partial x_{j}},$$
 (26)

with the following notations:

$$\vec{p}_{\text{fields}} = \int \epsilon_{\circ}(\vec{E} \times \vec{B}) d^3x = \frac{1}{c^2} \int d^3x \, \vec{S},$$
 (27)

which we associate to the momentum in the fields since it fulfills a similar role as $\vec{p}_{\rm mec}$, and

$$T_{ij} = \epsilon_{\circ} \left[E_i E_j + c^2 B_i B_j - \frac{1}{2} \left(\vec{E} \cdot \vec{E} + c^2 \vec{B} \cdot \vec{B} \right) \delta_{ij} \right], \quad (28)$$

which is the tensor of electromagnetic tensions.



Electromagnetic waves
Maxwell Equations
Electrodynamic potentials
Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

waves

Wave propagation in a medium



Electromagnetic waves Maxwell Equations

Maxwell Equations
Electrodynamic potentials
Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization

Quasi-monochromatic
waves

Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves

• For each component i the integrand of Eq. 26 (involving T_{ij}) can be seen as a divergence, so

$$\frac{d}{dt}(\vec{p}_{\text{mec}} + \vec{p}_{\text{fields}})|_{i} = \oint_{\mathcal{S}} \sum_{i} T_{ij} n_{j} d\mathcal{A}, \qquad (29)$$

where we recognize a flux integral over the surface bounding the volume \mathcal{V} .



Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasi-monochromatic waves

Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

wavee



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

2 Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer Polarization

Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative

transfer
Polarization
Quasi-monochromatic

waves
Wave propagation in a

medium Constitutive equations

2.1 Spectral decomposition

• In the absence of sources, if we decompose

$$\vec{E}(\vec{x},t) = \frac{1}{2\pi} \int d\omega \vec{E}(\vec{x},\omega) e^{i\omega t}, \qquad (30)$$

the Maxwell equations yield

$$(\nabla^2 + \mu \epsilon \omega^2) \left\{ \begin{array}{c} \vec{E} \\ \vec{B} \end{array} \right\} = 0. \tag{31}$$

- If ϵ and μ are both real, the solutions are $e^{\pm ikx}$, with $k=\sqrt{\mu\epsilon}\omega$
- We define the phase velocity $v_{\phi} = \frac{\omega}{k} = \frac{c}{n}$, where $n = \sqrt{\frac{\mu\epsilon}{\mu_0\epsilon_0}}$ is the refraction index.
- In general,

$$\left\{ \begin{array}{c} E_i \\ B_i \end{array} \right\} = \frac{1}{2\pi} \int d\omega \left\{ \begin{array}{c} \mathcal{E}_i \\ \mathcal{B}_i \end{array} \right\} e^{\pm i\vec{k}\cdot\vec{x} - iwt}, \tag{32}$$



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations

Poynting's theorem

Wave propagation in

vacuum Spectral decomposition

Connection with radiative transfer

Quasi-monochromatic waves

Polarization

Wave propagation in a medium

2.1 Spectral decomposition



We recognize d'Alembert's solution for the wave equation,

$$\left\{ \begin{array}{c} E_{i} \\ B_{i} \end{array} \right\} = \frac{1}{2\pi} \int d\omega \left\{ \begin{array}{c} \mathcal{E}_{i} \\ \mathcal{B}_{i} \end{array} \right\} e^{\pm ik(\hat{n}\cdot\vec{x} - v_{\phi}t)}, \quad (33)$$

where each component i has a form $f(\hat{n} \cdot \vec{x} - v_{\phi}t) + g(\hat{n} \cdot \vec{x} + v_{\phi}t)$, and where \hat{n} is the direction of propagation.

• Using Maxwell's equations (tarea), $\hat{n} \cdot \vec{\mathcal{E}} = 0$, $\hat{n} \cdot \vec{\mathcal{B}} = 0$ and $\vec{\mathcal{B}} = \frac{n}{c} \hat{n} \times \vec{\mathcal{E}}$.

Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization
Quasi-monochromatic

Wave propagation in a medium

2.1 Spectral decomposition

- For harmonic fields it is customary to use complex notation (because of the spectral decomposition), so that $\vec{S} = \Re(\vec{E}) \times \Re(\vec{H})$.
- In general for products of the type

$$\Re(ae^{-i\omega t})\Re(be^{-i\omega t}) = \frac{1}{2}\Re(a^*b + abe^{-2i\omega t}),$$
 (34)

it is also customary to take time averages $\langle (\cdots) \rangle_T = \lim_{T \to \infty} \frac{1}{T} \int_0^\infty (\cdots) dt$, and

$$\langle \Re(ae^{-i\omega t})\Re(be^{-i\omega t})\rangle = \frac{1}{2}\Re(a^*b). \tag{35}$$



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization

Quasi-monochromatic
waves

Wave propagation in a medium

2.1- Spectral decomposition

tee

We therefore have

$$\langle \vec{S} \rangle = \frac{1}{2} \vec{E} \times \vec{H}^* = \frac{1}{2} \sqrt{\frac{\epsilon}{\mu}} |\mathcal{E}|^2 \hat{n}.$$
 (36)

And similarly,

$$\langle u \rangle = \frac{1}{4} (\epsilon \vec{E} \cdot \vec{E}^* + \frac{1}{\mu} \vec{B} \cdot \vec{B}^*) = \frac{\epsilon}{2} |\mathcal{E}|^2.$$
 (37)

• Finally, $\langle \vec{\mathcal{S}} \rangle = v_{\phi} u \hat{n}$.

Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization
Quasi-monochromatic

Wave propagation in a medium



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization Quasi-monochromatic waves

Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition


Connection with radiative transfer


Polarization

Quasi-monochromatic waves

Wave propagation in a medium

2.2- Connection with radiative transfer





In radiative transfer notation, the flux density in direction k_o would be

$$F_{\nu}(\vec{x}) = \int d\Omega I_{\nu}(\hat{k}, \vec{x}) \, \hat{k} \cdot \hat{k}_{\circ}. \tag{38}$$

 Therefore the specific intensity field for a monochromatic plane wave is

$$I_{\nu}(\hat{k}) = \|\vec{S}\| \, \delta(\hat{k} - \hat{k}_{\circ}). \tag{39}$$



Electromagnetic waves
Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization Quasi-monochromatic waves

Wave propagation in a medium



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

2 Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization

Quasi-monochromatic waves

3 Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization

Quasi-monochromatic waves

Wave propagation in a

2.3 Polarization

 In summary, the electric field of a monochromatic wave can be decomposed in two linearly polarized waves,

$$\vec{E}(\vec{x},t) = (\hat{\epsilon}_1 E_1 + \hat{\epsilon}_2 E_2) e^{i(\vec{k}\cdot\vec{x} - \omega t)}, \tag{40}$$

whose total describes, in general, an eliptically polarized wave.

• With a change of vectorial basis to $\hat{\epsilon}_{\pm} = \frac{1}{\sqrt{2}}(\hat{\epsilon}_1 \pm i\hat{\epsilon}_2)$, we can also decompose \vec{E} in two circularly polarized waves,

$$\vec{E}(\vec{x},t) = (\hat{\epsilon}_{+}E_{+} + \hat{\epsilon}_{-}E_{-})e^{i(\vec{k}\cdot\vec{x}-\omega t)}.$$
 (41)



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition

Connection with radiative transfer

Polarization

Quasi-monochromatic waves

Wave propagation in a medium


2.3 Polarization

With the notation

$$\begin{split} E_1 &= \mathcal{E}_1 e^{i\phi_1}, \quad E_2 = \mathcal{E}_2 e^{i\phi_2}, \\ E_+ &= \mathcal{E}_+ e^{i\phi_+}, \quad E_- = \mathcal{E}_- e^{i\phi_-}, \end{split}$$

we have

 $\begin{cases} \text{linear polarization}: \phi_2 - \phi_1 = 0. \\ \text{circular polarization}: |\phi_2 - \phi_1| = \frac{\pi}{2} \text{ and } \mathcal{E}_2 = \mathcal{E}_1. \\ \text{the general case is eliptical, with}: \tan(\chi) = \frac{\mathcal{E}_1}{\mathcal{E}_2} \frac{\cos(\phi_1)}{\cos(\phi_2)}. \end{cases}$





Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

olarization

Quasi-monochromatic waves

Wave propagation in a medium

2.3 Polarization

 It is customary to use the Stokes parameters to characterize the polarization state of monochromatic light:

$$I = E_{1}E_{1}^{*} + E_{2}E_{2}^{*} = \mathcal{E}_{1}^{2} + \mathcal{E}_{2}^{2},$$


$$Q = E_{1}E_{1}^{*} - E_{2}E_{2}^{*} = \mathcal{E}_{1}^{2} - \mathcal{E}_{2}^{2},$$

$$U = E_{1}E_{2}^{*} - E_{2}E_{1}^{*} = 2\mathcal{E}_{1}\mathcal{E}_{2}\cos(\phi_{2} - \phi_{1}),$$

$$V = i(E_{1}E_{2}^{*} - E_{2}E_{1}^{*}) = 2\mathcal{E}_{1}\mathcal{E}_{2}\sin(\phi_{2} - \phi_{1}).$$

$$(42)$$

- We see that Stokes I (the total "radiance") is $I \propto |\vec{S}|$, Q and U measure linear polarization, while V measure circular polarization. In order to make this obvious it is best to use mental experiments with polarizors that select specific types of polarization (see class).
- For a strictly monochromatic wave, it follows that





Electromagnetic waves

Maxwell Equations

Electrodynamic potentials

Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization

Quasi-monochromatic waves

Wave propagation in a medium



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

2 Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic waves

3 Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a medium

2.4 Quasi-monochromatic waves

• In order to obtain $\vec{E}(\vec{x}, \omega)$, we need to know $\vec{E}(t)$ for all t, since

$$\vec{E}(\vec{x},\omega) = \int_{-\infty}^{+\infty} \vec{E}(\vec{x},t)e^{i\omega t}dt.$$
 (44)

 So in practice, we treat E₁ and E₂ as random variables, i.e. for a wave in vacuum, described by Eq. 40,

$$\vec{E}(\vec{x},t) = (E_1(t)\hat{e}_1 + E_2(t)\hat{e}_2)e^{i(\vec{k}\cdot\vec{x}-\omega t)}.$$
 (45)

Alternatively we can also replace the time dependence in Eq. 45 with a probability density, which itself may depend on time.

• To fix ideas, let's remember that $\Delta t \Delta \omega = 1$ for Gaussian spectra, where Δt is the 'coherence time', and $\Delta \omega$ is the 'bandwidth' of the quasi-monochromatic wave.



Electromagnetic waves
Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a medium

2.4 Quasi-monochromatic waves

 In order to measure the Stokes parameters, we need averages of the kind

$$\langle E_1 E_2^* \rangle = \lim_{T \to \infty} \frac{1}{T} \int dt E_1(t) E_2^*(t) dt. \tag{46}$$

We therefore have

$$\begin{split} \langle Q^2 \rangle + \langle U^2 \rangle + \langle V^2 \rangle &= \langle I^2 \rangle - \\ 4(\langle \mathcal{E}_1^2 \rangle \langle \mathcal{E}_2^2 \rangle - \langle \mathcal{E}_1 \mathcal{E}_2 e^{i(\phi_2 - \phi_1)} \rangle \langle \mathcal{E}_1 \mathcal{E}_2 e^{-i(\phi_2 - \phi_1)} \rangle \\ &= \langle I^2 \rangle - \\ 4(\langle \mathcal{E}_1^2 \rangle \langle \mathcal{E}_2^2 \rangle - \langle \mathcal{E}_1^2 \mathcal{E}_2^2 \cos^2(\phi_2 - \phi_1) \rangle - \langle \mathcal{E}_1^2 \mathcal{E}_2^2 \cos^2(\phi_2 - \phi_1) \rangle), \end{split}$$

$$(47)$$

and, by Shwartz' inequality $(\langle ab \rangle \leq \langle a \rangle \langle b \rangle)$,

$$I^2 \ge Q^2 + U^2 + V^2. \tag{48}$$



Electromagnetic waves Maxwell Equations

Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a medium

2.4- Quasi-monochromatic waves

- For a wave with a single and constant eliptical polarization state, then the equality holds in Eq. 48.
- On the other hand, for a completely unpolarized wave,
 Q = U = V = 0.
- The Stokes parameters are additive. Proof: consider a sum of N different waves

$$\vec{E} = \sum_{k=1}^{N} \vec{E}^{k} = \sum (\hat{\epsilon}_{1} E_{1}^{k} + \hat{\epsilon}_{2} E_{2}^{k}) e^{i(\vec{k} \cdot \vec{x} - \omega t)}.$$
 (49)

Because each $E_i^k(t)$ is statistically independent, $\langle E_i^k E_i^{l*} \rangle = \delta_{kl} \langle E_i^k E_i^{k*} \rangle$, and

$$\begin{pmatrix} I \\ Q \\ U \\ V \end{pmatrix} = \sum_{k} \begin{pmatrix} I_{k} \\ Q_{k} \\ U_{k} \\ V_{k} \end{pmatrix}. \tag{50}$$



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization

Quasi-monochromatic waves Wave propagation in a

2.4- Quasi-monochromatic waves

 We can therefore decompose an arbitrary set of Stokes parameters in

$$\begin{pmatrix} I \\ Q \\ U \\ V \end{pmatrix} = \begin{pmatrix} I - \sqrt{Q^2 + U^2 + V^2} \\ 0 \\ 0 \\ 0 \end{pmatrix} +$$

$$\overbrace{\begin{pmatrix}
\sqrt{Q^2 + U^2 + V^2} \\
Q \\
U \\
V
\end{pmatrix}}. (51)$$

• The first term 'unpol' is completely unpolarized since Q = U = V = 0, while the second term 'pol' is completely polarized since it satisfies $I^2 = Q^2 + U^2 + V^2$ (Eq. 43).



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a medium

2.4- Quasi-monochromatic waves



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization

Quasi-monochromatic waves

Wave propagation in a medium

- The total polarized intensity of a wave train is thus be $I^{\text{pol}} = \sqrt{Q^2 + U^2 + V^2}$.
- We define the polarization fraction as

$$\Pi = \frac{I^{\text{pol}}}{I}.$$
 (52)



Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

2 Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Ouasimonochromatic waves

3 Wave propagation in a medium

Constitutive equations Kramers-Kronig relations Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Nave propagation

waves



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

2 Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

3 Wave propagation in a medium

Constitutive equations

Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a

medium

Constitutive equations

• Each monochromatic component of the field \vec{E} , \vec{B} must fulfill the following constitutive relations:

$$\vec{P} = \epsilon_{\circ} \chi \vec{E} \longrightarrow \vec{P}(\omega) = \epsilon_{\circ} \chi(\omega) \vec{E}(\omega),$$

$$\vec{B} = \mu \vec{H} \longrightarrow \vec{B}(\omega) = \mu(\omega) \vec{H}(\omega),$$

$$\vec{J} = \sigma \vec{E} \longrightarrow \vec{J}(\omega) = \sigma(\omega) \vec{E}(\omega),$$
(53)

in which we have added Ohm's law.

• We note that $\chi(-\omega) = \chi^*(\omega)$, so that $\chi(t) = \frac{1}{2\pi} \int d\omega \chi(\omega) \exp(-i\omega t)$ be real (and similarly for μ and σ).



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Povnting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic Wave propagation in a

waves

medium

Constitutive equations

• The Fourier convolution theorem states that if $X(\omega) = Y(\omega)Z(\omega)$, then

$$X(t) = \int_{-\infty}^{\infty} Y(t - t') Z(t') dt', \tag{54}$$

where $Y(t) = \frac{1}{2\pi} \int d\omega Y(\omega) \exp(-i\omega t)$, etc..

• Applying the convolution theorem to χ (for example),

$$P(t) = \int_{-\infty}^{\infty} G(t - t') E(t') dt'$$
, with
$$G(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} \epsilon_{\circ} \chi(\omega) e^{-i\omega t} d\omega. \quad (55)$$



Electromagnetic waves

Maxwell Equations Electrodynamic potentials Wave equations Poynting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer Polarization

Quasi-monochromatic waves

Wave propagation in a

Constitutive equations

Kramers-Kronig relations Monochromatic waves

medium

- We see that P(t) depends on the history of $\vec{E}(t')$, which bears physical sense only in the past, for t' < t, so G(t) = 0 if t < 0. We will use this property in the next section.
- This time we write the monochromatic wave as

$$\vec{E}(t) = \vec{A}\cos(\omega_{\circ}t) + \vec{B}\sin(\omega_{\circ}t) = \Re(\vec{E}_{c}(t)), \quad (56)$$

with $\vec{E}_c = (\vec{A} - i\vec{B})(\cos(\omega_{\circ}t) + i\sin(\omega_{\circ}t)).$

In the Fourier plane,

$$E(\omega) = \pi \left[(A + iB)\delta(\omega - \omega_{\circ}) + (A - iB)\delta(\omega + \omega_{\circ}) \right]. \quad (57)$$

We can evaluate

$$P(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} \epsilon_{\circ} \chi(\omega) E(\omega) e^{-i\omega t} d\omega$$
$$= \Re \left[\frac{\epsilon_{\circ}}{2} (A - iB) \chi(\omega_{\circ}) e^{-i\omega_{\circ} t} \right] = \Re [P_{c}(t)], \quad (58)$$

using $\chi(-\omega) = \chi^*(\omega)$, and where $P_c = \epsilon_{\circ} \chi(\omega_{\circ}) E_c(t)$.



Electromagnetic waves Maxwell Equations

Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

waves

Constitutive equations Kramers-Kronig relations Monochromatic waves

42

 With the spectral decomposition of the constitutive relations we can rewrite the Maxwell equations in their harmonic versions. In the absence of free charges,

$$\vec{\nabla} \cdot \vec{E}(\omega) = 0, \quad \vec{\nabla} \times \vec{E}(\omega) = -i\omega\mu(\omega)\vec{H}(\omega), \vec{\nabla} \cdot \vec{H}(\omega) = 0, \quad \vec{\nabla} \times \vec{H}(\omega) = -i\omega\epsilon(\omega)\vec{E}(\omega),$$
(59)

where (tarea)

$$\epsilon(\omega) = \epsilon_{\circ}(1 + \chi(\omega)) + i\frac{\sigma(\omega)}{\omega}.$$
 (60)

• Note that both susceptibility and conductivity contribute to the imaginary part of ϵ :

$$\Im(\epsilon) = \epsilon_{\circ}\Im(\chi) + \Re(\sigma/\omega). \tag{61}$$



Electromagnetic waves

Maxwell Equations

Electrodynamic potentials

Wave equations

Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a

medium

Constitutive equations

Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic waves

3 Wave propagation in a medium

Constitutive equations

Kramers-Kronig relations

Monochromatic waves



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

waves
Wave propagation in a

medium Constitutive equations


3.2 Kramers-Kronig relations

 From physical considerations we can anticipate that the induced P(t) depends on the history of the applied field, or

$$\vec{P}(t) = \int_{-\infty}^{\infty} G(t, t') \vec{E}(t') dt'$$
 (62)

(note difference with Eq. 55).

- Let's assume that $\vec{E} = \delta(t t_{\circ})\vec{E}_{\circ}$. Then $\vec{P}(t) = G(t, t_{\circ})\vec{E}_{\circ}$, and G is the polarization resulting from a delta-unitary electric field.
- If the properties of the medium do not change in time, $G(t, t_{\circ}) = G(t t_{\circ})$, and we recover Eq. 55.
- Causality requires that $G(\tau) = 0$ if $\tau < 0$, so





Electromagnetic waves
Maxwell Equations
Electrodynamic potentials
Wave equations
Povntino's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

waves

3.2 Kramers-Kronig relations

• We extend Eq. 63 to the complex plane with $\tilde{\omega} = \omega_R + i\omega_I$, where $\omega_I > 0$.

$$\epsilon_{\circ}\chi(\tilde{\omega}) = \int_{0}^{\infty} dt G(t) e^{i\tilde{\omega}t}.$$
 (64)

- If $\int_0^\infty |G(t)| dt$ converges, so does $\int_0^\infty G(t) e^{i\tilde{\omega}t} dt$, and $\chi(\tilde{\omega})$ is analytical in the superior $\mathbb C$ plane $(\omega_I > 0)$.
- Therefore $\chi(\tilde{\omega})/(\tilde{\omega}-\omega)$ is analytical except in the pole $\tilde{\omega}=\omega$, where ω is a point along the real axis.
- We can apply the Kramers-Kronig theorem (proof: see Bohren & Huffman, Sec. 2.3.2), which gives

$$i\pi\chi(\omega) = P \int_{-\infty}^{\infty} \frac{\chi(\Omega)}{\Omega + \omega} d\Omega,$$
 (65)

where P indicates Cauchy's 'principal value'

$$P \int_{-\infty}^{\infty} \frac{\chi(\Omega)}{\Omega + \omega} d\Omega = \lim_{a \to 0} \left(\int_{-\infty}^{\omega - a} \frac{\chi(\Omega)}{\Omega + \omega} d\Omega + \int_{\omega + a}^{\infty} \frac{\chi(\Omega)}{\Omega + \omega} d\Omega \right). \quad (66)$$



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

waves

3.2 Kramers-Kronig relations

Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition Connection with radiative transfer

Polarization Quasi-monochromatic waves

Wave propagation in a medium

Constitutive equations

Kramers-Kronig relations
Monochromatic waves

• Using that $\chi^*(\Omega) = \chi(-\Omega)$ we can restrict the integration to $\Omega > 0$, and use $\chi = \chi_R + i\chi_I$ to rewrite Eq. 66:

$$\chi_R(\omega) = \frac{2}{\pi} P \int_0^\infty \frac{\Omega \chi_I(\Omega)}{\Omega^2 - \omega^2} d\Omega,$$
(67)

$$\chi_I(\omega) = -\frac{2\omega}{\pi} P \int_0^\infty \frac{\chi_R(\Omega)}{\Omega^2 - \omega^2} d\Omega.$$
 (68)

• Similar relationships exists for μ y σ .



Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

3 Wave propagation in a medium

Constitutive equations
Kramers-Kronig relations
Monochromatic waves



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum Spectral decomposition

Connection with radiative transfer Polarization

Quasi-monochromatic

Wave propagation in a medium

waves

3.3 Monochromatic waves

 We now extend the monochromatic waves to homogeneous media. We inject

$$\vec{E}_c = \vec{E}_{\circ} e^{i(\vec{k}\cdot\vec{x}-\omega t)}$$
, and $\vec{H}_c = \vec{H}_{\circ} e^{i(\vec{k}\cdot\vec{x}-\omega t)}$, (69)

into Maxwell's equations.

• Allowing for $\vec{k} \in \mathbb{C}$, $\vec{k} = \underbrace{(k_R + ik_I)}_{k} \hat{e}$,

$$\vec{E}_c = \vec{E}_{\circ} e^{-\vec{k}_l \cdot \vec{x}} e^{i(\vec{k}_{\vec{R}} \cdot \vec{x} - \omega t)}. \tag{70}$$

The harmonic Maxwell equations (Eqs. 59) yield:

$$\vec{k} \cdot \vec{E}_{\circ} = 0 \qquad \vec{k} \cdot \vec{H}_{\circ}(\omega) = 0 \vec{k} \times \vec{E}_{\circ} = \omega \mu \vec{H}_{\circ}, \quad \vec{k} \times \vec{H}_{\circ} = -\omega \epsilon \vec{E}_{\circ}.$$
 (71)

• And with $\vec{k} \cdot \vec{k} = \omega^2 \epsilon \mu$,

$$k_R^2 - k_I^2 + 2i\vec{k}_I \cdot \vec{k}_R = \omega^2 \epsilon \mu$$
 (tarea). (72)



Electromagnetic waves Maxwell Equations

Maxwell Equations
Electrodynamic potentials
Wave equations
Poynting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization
Quasi-monochromatic

Wave propagation in a medium

3.3 Monochromatic waves

For a homogeneous wave (no free charges),

$$\vec{k} = \underbrace{(k_R + ik_I)}_{k} \hat{e},$$

and $k = \omega N/c$, where N is the complex refractive index,

$$N = c\sqrt{\epsilon\mu} = \sqrt{rac{\epsilon\mu}{\epsilon_{\circ}\mu_{\circ}}}.$$

- We set $N = n + i\kappa$, where n and κ are both $\in \mathbb{R}^+$.
- Eq. 70 gives:

$$\vec{E}_c = \vec{E}_{\circ} e^{-\frac{2\pi}{\lambda}\kappa z} e^{i(\frac{2\pi nz}{\lambda} - i\omega t)}.$$
 (73)

• \Rightarrow the imaginary part of *N* corresponds to absorption.



Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative transfer
Polarization

Quasi-monochromatic waves

Wave propagation in a

medium Constitutive equations

3.3 Monochromatic waves



• We can apply the Kramers-Kronig relations to $(N(\omega) - 1)$ (the -1 is motivated by $\lim_{\omega \to \infty} N(\omega) = 1$):

$$n(\omega) - 1 = \frac{2}{\pi} P \int_0^\infty \frac{\Omega \kappa(\Omega)}{\Omega^2 - \omega^2} d\Omega$$

$$\kappa(\omega) = -\frac{2\omega}{\pi} P \int_0^\infty \frac{n(\Omega)}{\Omega^2 - \omega^2} d\Omega$$
(74)

 We see that the absorption in a medium is also related to the real refractive index.

Electromagnetic waves

Maxwell Equations
Electrodynamic potentials
Wave equations
Povnting's theorem

Wave propagation in vacuum

Spectral decomposition
Connection with radiative
transfer
Polarization

Quasi-monochromatic

Wave propagation in a